

# Adjustable Angle Side, Front or Rear Mount Camera

**User Manual** 



#### EchoMaster.com

EchoMaster is a Power Brand of AAMP Global

Woolmer Way, Bordon, Hampshire, GU35 9QE, United Kingdom

15500 Lightwave Drive, Suite 202 Clearwater, Florida 33760

email - support@aampglobal.com (Europe) email - technical.eu@aampglobal.com (Europe)



### Introduction

Thank you for purchasing your EchoMaster Pro automotive camera.

This manual covers the following part numbers

- ► PCAM-360-P
- ► PCAM-360-N

EchoMaster Pro cameras are designed to improve safety during driving by providing high quality images of surrounding areas and obstacles in the vicinity of the vehicle. They will also improve vehicle maneuvering capability by displaying blind spots not normally visible to the driver.

Please ensure you read and understand all aspects of this manual before fitting or using your EchoMaster Pro Camera. Choose a suitable mounting place dependent on the application. Ensure that there are no wiring harnesses or hoses/pipes located behind this panel before drilling.


# **Key Features**

- ▶ 1/4" CMOS Sensor
- Operates at 0.3 LUX
- IP67 Rated
- ▶ 170° Viewing Angle
- Selectable Image (mirrored/non-mirrored)

#### **Box Contents**

- Camera
- Manual
- Mounting Hardware
- Hole Saw
- Harness
- Angle Adjustment Tool

## **Dimensions (mm/in)**



### **Specification**

	PCAM-360-P	I PCAM-360-N	
Sensor Type	1/4"(	1/4" CMOS	
LEDs		0	
Illumination	0.3	0.3 LUX	
Viewing Angle	170 d	170 degrees	
Mirror Image	Y	YES	
Normal View	Y	YES	
Water/Debris-Proof	IF	IP67	
Audio	N	NO	
Power Supply	9-16	9-16V DC	
Current	<50	<50mA	
Working Temperature	-30°C	-30°C - +70°C	
Dimensions (mm)	D (21) x W	D (21) x W (25) x H (25)	
System	PAL	NTSC	
TV Lines	420	420	
Resolution	648 x 488	648 x 488	

# Wiring Diagram & Pin Out

